
### To open the filter chamber



## To close the filter chamber



HEPA filter

**G600** 

DLX OPERATING & FILTER REPLACEMENT DIRECTIONS

Airpura \_\_\_\_\_

# TO BEGIN USING YOUR

**Inspect the exterior of your Airpura** to verify there is no damage from shipping. If any damage is noted, please follow the instructions from the distributor returns policy.

Wipe the unit with a damp cloth to remove any dust from packaging

Plug the unit into a regular grounded 110 volt outlet

Turn on the unit to MAX and allow it to run for a few minutes

Set the variable speed control to the level you wish

The most efficient way to use your Airpura for regular air quality maintenance is to run it at a low speed **24 hours a day 7 days a week.** 



# FILTER MAINTENANCE AND REPLACEMENT

#### **The Prefilter**

Can be vacuumed from the exterior of the unit once a month or more often. Should be replaced at least after 12 months of use


#### To vacuum the Prefilter

Use the brush attachment on your vacuum cleaner Vacuum slowly around the mesh surface of the filter chamber

## **IMPORTANT SAFETY NOTE**

Please ensure air purifier is turned OFF when plugging into a power source. Failure to do so may result in motor potentially stalling and/or burning.





**Poly Prefilter C600 2PK** 12 months HepaBarrier 600CT Filter (95 % efficient @ 1 Microns) 12-16 months

**26 lbs German Carbon Filter** 12-24 months

## **Technical specifications**

Odors, airborne chemical control 26 lbs German Carbon Filter 13"H in x 13.25"OD in x 7"ID

Carbon Bed 3" deep

Particle removal HepaBarrier

**Air Flow 560 cfm** More cfm than any other home unit available

**Prefilter** 570 in<sup>2</sup> x 1 in

**Housing** Powder coat steel **Size** 23 in x 15 in

**Weight** 45 lbs total

Watts 120 on high / 40 on low

Sound Level 28.1 db on low (at 6 feet) 62.3 db on high (560 cfm) (Room Level 25.1)

ETL Certified Conforms to CSA C22.2 no 113 ANSI / UL 507



## Air purifiers models and filter configurations

	Prefilter	Carbon
Alternates	Cotton Prefilter TarBarrier Prefilter	26 lbs anthracite Carbon filter 100% 26 lbs coconut shell carbon filter